

钍地半导体
Tudi Semiconductor

Product Specification

TUDI-DS34C86

DS34C86 Quad CMOS Differential Line Receiver

网址 www.sztdbdt.com

用芯智造·卓越品质

semiconductor device manufacturer

- Design
- research and development
- production
- and sales


Features

- Low power CMOS design ± 0.2V sensitivity over the entire common mode range
- Typical propagation delays: 20 ns
- Typical input hysteresis: 50 mV
- Inputs won't load line when Vcc = 0V
- Meets the requirements of EIA standard RS-422
- TRI-STATE outputs for connection to system buses

General Description


The DS34C86 is a quad differential line receiver designed to meet the RS-422, RS-423, and Federal Standards 1020 and1030 for balanced and unbalanced digital data transmission, while retaining the low power characteristics of CMOS.
The DS34C86 has an input sensitivity of 200 mV over the common mode input voltage range of ± 7V. Hysteresis is provided to improve noise margin and discourage output instability for slowly changing input waveforms.
Separate enable pins allow independent control of receiver pairs. The TRI-STATE ®outputs have 6 mA source and sink capability. The DS34C86 is pin compatible with the DS3486.

Logic Diagram



Connection Diagram

DIP-16/SOP-16/TSSOP-16



Top Vlew

Absolute Maximum Ratings (Notes 1 & 2)

Condition	Min	Max	UNITS
Supply Voltage (Vcc)	-	7	V
Common Mode Range (V_{CM})	-14	+14	V
Differentlal Input Voltage (V_{DIFF})	-14	+14	V
Enable Input Voltage (V_{IN})	-	7	V
Storage Temperature Range (T_{STG})	-65	+150	°C
Lead Temperature (Soldering 10 sec)	-	260	°C
Current Per Output	-25	+25	mA
Operating Conditions			
Supply Voltage (Vcc)	4.75	5.25	V
Operating Temperature Range (T_A)	-40	+85	°C
Enable Input Rise or Fall Times	-	500	ns

DC Electrical Characteristics

Vcc = 5V +5% (unless otherwise specified) (Note 3)

Symbor	Parameter	Conditions	Min	Typ	Max	Unlts
V_{TH}	Minimum Differential Input Voltage	V_{OUT} = V_{OH} or V_{OL} -7V <V_{CM} <+7V	-0.2		+0.2	V
R_{IN}	Input Resistance	-7V <V_{CM} < +7V (One Input AC GND)		10		kΩ
I_{IN}	Input Current (Under Test)	V_{IN} = +10V, Other Input GND V_{IN}= -10V, Other Input = GND		+1.1 -1.6		mA mA
V_{OH}	Minimum High Level Output Voltage	V_{CC}=Min,$V_{(DIFF)}$=+1V I_{OUT}=6.0mA	3.84	4.2		V
V_{OL}	Maximum Low Lever Output Voltage	V_{CC}=Max,$V_{(DIFF)}$=+1V I_{OUT}=6.0mA				V
V_{IH}	Minimum Enable High Input Level Voltage		2.0			V
V_{IL}	Maximum Enable Low Input Level Voltage				0.8	V
I_{OZ}	Maximum TRI-STATE Output Leakage Current	V_{OUT}=V_{CC} or GND, TRI-STATE Control=VIL		±0.5	±5.0	μA
I_I	Maximum Enable Input Current	V_{IN}=V_{CC} or GND			±1.0	μA
I_{CC}	Qulescent Power Supply Current	V_{CC}=Max,$V_{(DIFF)}$=+1V		12		mA
V_{HYST}	Input Hysteresis			50		mV

AC Electrical Characteristics

V_{CC} = 5V ±5% (unless otherwise specified) (Note 3)


Symbor	Parameter	Conditions	Min	Typ	Max	Unlts
T_{PLH}, t_{PHL}	Propagation Delay Input to Output	C_L=50pF V_{DIFF}=2.5V		20		ns
t_{PLZ}, t_{PHZ}	Propagation Delay TRI-STATE Control to Output	C_L=50pF R_L+1000Ω V_{DIFF}=2.5v		12		ns
t_{PZL}, t_{PZH}	Propagation Delay TRI-STATE Control to Output	C_L=50pF R_L=1000Ω V_{DIFF}=2.5V		14		ns

Note 1: Absolute Maximum Ratings indicate limits beyond which damage to the device may occur. Operating Ratings indicate conditions for which the device is intended to be functional, but specific performance is not ensured.


Note 2: Unless otherwise specifled, all voltages are referenced to ground.

Note 3: Unless otherwise specified, Min/Max limits apply across the -40°C to +65°C temperature ranger All typicals are given for Vca 5V and TA = 25°C.

Propagation Delay



Test Circuit for TRI-STATE Output Tests




CL = Includes load and test jig capacitance.

S1 =Vcc for tpzu, and tpLz measurements.

S1 = GND for tPzH, and tpHz measurements.


TRI-STATE Output Enable and Disable Waveforms





Order information

Order Number	Package	Package Quantity	Marking On The park
DS34C86N-TUDI	DIP16	Tube,25,A box of 1000	DS34C86N

Package DIP16







SIZE / SYMBOL	MIN./mm	MAX./mm
A2	3.20	3.60
A1	0.51	___
A	3.60	5.33
L	3.00	3.60
b	0.36	0.56
B1	1.52	
D	18.80	19.94
E1	6.20	6.60
e	2.54	
C	0.20	0.36
eB	7.62	9.30
R	0.20TYP	
R1	0.30TYP	
θ	0°	8°
θ1	45°TYP	
02	12°TYP	
03	0°	8°
04	0°	10°

Important statement:

●TUDI Semiconductor reserves the right to modify the product manual without prior notice! Before placing an order, customers need to confirm whether the obtained information is the latest version and verify the completeness of the relevant information.

●Any semi-guide product is subject to failure or malfunction under specified conditions. It is the buyer's responsibility to comply with safety standards when using TUDI Semiconductor products for system design and whole machine manufacturing.And take the appropriate safety measures to avoid the potential in the risk of loss of personal injury or loss of property situation!

●TUDI Semiconductor products have not been licensed for life support, military, and aerospace applications,and therefore TUDI Semiconductor is not responsible for any consequences arising from the use of this product in these areas.

●If any or all TUDI Semiconductor products (including technical data, services) described or contained in this document are subject to any applicable local export control laws and regulations, they may not be exported without an export license from the relevant authorities in accordance with such laws.

●The specifications of any and all TUDI Semiconductor products described or contained in this document specify the performance, characteristics, and functionality of said products in their standalone state, but do not guarantee the performance, characteristics, and functionality of said products installed in Customer's products or equipment. In order to verify symptoms and conditions that cannot be evaluated in a standalone device, the Customer should ultimately evaluate and test the device installed in the Customer's product device.

●TUDI Semiconductor documentation is only allowed to be copied without any alteration of the content and with the relevant authorization.TUDI Semiconductor assumes no responsibility or liability for altered documents.

●TUDI Semiconductor is committed to becoming the preferred semiconductor brand for customers, and TUDI Semiconductor will strive to provide customers with better performance and better quallity products.