

- State-of-the-Art Advanced BiCMOS Technology (ABT) Design for 3.3-V Operation and Low-Static Power Dissipation
- Support Mixed-Mode Signal Operation (5-V Input and Output Voltages With 3.3-V V_{CC})
- Support Unregulated Battery Operation Down to 2.7 V
- Typical V_{OLP} (Output Ground Bounce) < 0.8 V at V_{CC} = 3.3 V, T_A = 25°C
- ESD Protection Exceeds 2000 V Per MIL-STD-883C, Method 3015; Exceeds 200 V Using Machine Model (C = 200 pF, R = 0)
- Latch-Up Performance Exceeds 500 mA Per JEDEC Standard JESD-17
- Bus-Hold Data Inputs Eliminate the Need for External Pullup Resistors
- Support Live Insertion
- Package Options Include Plastic Small-Outline (DW), Shrink Small-Outline (DB), and Thin Shrink Small-Outline (PW) Packages, Ceramic Chip Carriers (FK), and Ceramic (J) DIPs

SN54LVT240 . . . J PACKAGE
SN74LVT240 . . . DB, DW, OR PW PACKAGE
(TOP VIEW)



SN54LVT240 . . . FK PACKAGE
(TOP VIEW)



description

These octal buffers and line drivers are designed specifically for low-voltage (3.3-V) V_{CC} operation, but with the capability to provide a TTL interface to a 5-V system environment.

These devices are organized as two 4-bit buffer/line drivers with separate output-enable ($\overline{OE}$) inputs. When $\overline{OE}$ is low, the devices pass data from the A inputs to the Y outputs. When $\overline{OE}$ is high, the outputs are in the high-impedance state.

Active bus-hold circuitry is provided to hold unused or floating data inputs at a valid logic level.

To ensure the high-impedance state during power up or power down, $\overline{OE}$ should be tied to V_{CC} through a pullup resistor; the minimum value of the resistor is determined by the current-sinking capability of the driver.

The SN74LVT240 is available in TI's shrink small-outline package (DB), which provides the same I/O pin count and functionality of standard small-outline packages in less than half the printed-circuit-board area.

The SN54LVT240 is characterized for operation over the full military temperature range of –55°C to 125°C. The SN74LVT240 is characterized for operation from –40°C to 85°C.


UNLESS OTHERWISE NOTED this document contains PRODUCTION DATA information current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

Copyright © 1995, Texas Instruments Incorporated

FUNCTION TABLE
(each buffer)


INPUTS		OUTPUT
$\overline{OE}$	A	Y
L	H	L
L	L	H
H	X	Z

logic symbol†



† This symbol is in accordance with ANSI/IEEE Std 91-1984 and IEC Publication 617-12.

logic diagram (positive logic)



absolute maximum ratings over operating free-air temperature range (unless otherwise noted)†

Supply voltage range, V_{CC} ..... −0.5 V to 4.6 V
Input voltage range, V_I (see Note 1) ..... −0.5 V to 7 V
Voltage range applied to any output in the high state or power-off state, V_O (see Note 1) .... −0.5 V to 7 V
Current into any output in the low state, I_O: SN54LVT240 ..... 96 mA
SN74LVT240 ..... 128 mA
Current into any output in the high state, I_O (see Note 2): SN54LVT240 ..... 48 mA
SN74LVT240 ..... 64 mA
Input clamp current, I_{IK} ($V_I < 0$) ..... −50 mA
Output clamp current, I_{OK} ($V_O < 0$) ..... −50 mA
Maximum power dissipation at T_A = 55°C (in still air) (see Note 3): DB package ..... 0.6 W
DW package ..... 1.6 W
PW package ..... 0.7 W
Storage temperature range, T_{stg} ..... −65°C to 150°C

† Stresses beyond those listed under "absolute maximum ratings" may cause permanent damage to the device. These are stress ratings only, and functional operation of the device at these or any other conditions beyond those indicated under "recommended operating conditions" is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

NOTES: 1. The input and output negative-voltage ratings may be exceeded if the input and output clamp-current ratings are observed.
2. This current flows only when the output is in the high state and $V_O > V_{CC}$.
3. The maximum package power dissipation is calculated using a junction temperature of 150°C and a board trace length of 750 mils. For more information, refer to the *Package Thermal Considerations* application note in the 1994 *ABT Advanced BiCMOS Technology Data Book*, literature number SCBD002B.

recommended operating conditions (see Note 4)

			SN54LVT240		SN74LVT240		UNIT
			MIN	MAX	MIN	MAX	
V_{CC}	Supply voltage		2.7	3.6	2.7	3.6	V
V_{IH}	High-level input voltage		2		2		V
V_{IL}	Low-level input voltage			0.8		0.8	V
V_I	Input voltage			5.5		5.5	V
I_{OH}	High-level output current			−24		−32	mA
I_{OL}	Low-level output current			48		64	mA
$\Delta t/\Delta v$	Input transition rise or fall rate	Outputs enabled		10		10	ns/V
T_A	Operating free-air temperature		−55	125	−40	85	°C

PRODUCT PREVIEW

NOTE 4: Unused control inputs must be held high or low to prevent them from floating.

PRODUCT PREVIEW information concerns products in the formative or design phase of development. Characteristic data and other specifications are design goals. Texas Instruments reserves the right to change or discontinue these products without notice.

electrical characteristics over recommended operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS			SN54LVT240			SN74LVT240			UNIT
				MIN	TYP†	MAX	MIN	TYP†	MAX	
V_{IK}	V_{CC} = 2.7 V,	I_I = −18 mA				−1.2			−1.2	V
V_{OH}	V_{CC} = MIN to MAX‡,	I_{OH} = −100 µA		V_{CC}−0.2			V_{CC}−0.2			V
	V_{CC} = 2.7 V,	I_{OH} = − 8 mA		2.4			2.4			
	V_{CC} = 3 V	I_{OH} = − 24 mA		2						
		I_{OH} = −32 mA					2			
V_{OL}	V_{CC} = 2.7 V	I_{OL} = 100 µA				0.2			0.2	V
		I_{OL} = 24 mA				0.5			0.5	
	V_{CC} = 3 V	I_{OL} = 16 mA				0.4			0.4	
		I_{OL} = 32 mA				0.5			0.5	
		I_{OL} = 48 mA				0.55				
		I_{OL} = 64 mA							0.55	
I_I	V_{CC} = 0 or MAX‡,	V_I = 5.5 V				10			10	µA
	V_{CC} = 3.6 V	V_I = V_{CC} or GND	Control inputs			±1			±1	
		V_I = V_{CC}	Data inputs			1			1	
		V_I = 0				−5			−5	
I_{off}	V_{CC} = 0,	V_I or V_O = 0 to 4.5 V							±100	µA
$I_{I(hold)}$	V_{CC} = 3 V	V_I = 0.8 V	Data Inputs	75			75			µA
		V_I = 2 V		−75			−75			
I_{OZH}	V_{CC} = 3.6 V,	V_O = 3 V				5			5	µA
I_{OZL}	V_{CC} = 3.6 V,	V_O = 0.5 V				−5			−5	µA
I_{CC}	V_{CC} = 3.6 V, V_I = V_{CC} or GND	I_O = 0,	Outputs high		0.12	0.19		0.12	0.19	mA
			Outputs low		8.6	12		8.6	12	
			Outputs disabled		0.12	0.19		0.12	0.19	
ΔI_{CC}§	V_{CC} = 3 V to 3.6 V, Other inputs at V_{CC} or GND	One input at V_{CC} − 0.6 V,				0.2			0.2	mA
C_I	V_I = 3 V or 0				4			4		pF
C_o	V_O = 3 V or 0				8			8		pF

† All typical values are at V_{CC} = 3.3 V, T_A = 25°C.
‡ For conditions shown as MIN or MAX, use the appropriate value specified under recommended operating conditions.
§ This is the increase in supply current for each input that is at the specified TTL voltage level rather than V_{CC} or GND.

PRODUCT PREVIEW

PRODUCT PREVIEW information concerns products in the formative or design phase of development. Characteristic data and other specifications are design goals. Texas Instruments reserves the right to change or discontinue these products without notice.

switching characteristics over recommended ranges of supply voltage and operating free-air temperature, C_L = 50 pF (unless otherwise noted) (see Figure 1)


PARAMETER	FROM (INPUT)	TO (OUTPUT)	SN54LVT240				SN74LVT240				UNIT
			V_{CC} = 3.3 V ± 0.3 V		V_{CC} = 2.7 V		V_{CC} = 3.3 V ± 0.3 V			V_{CC} = 2.7 V	
			MIN	MAX	MIN	MAX	MIN	TYP†	MAX	MIN MAX	
t_{PLH}	A	Y	1	4.2		5.2	1	2.9	4.1	5.2	ns
t_{PHL}			1.3	3.7		4.1	1.3	2.5	3.5	4	
t_{PZH}	$\overline{OE}$	Y	1.2	4.7		5.7	1.2	3.2	4.6	5.6	ns
t_{PZL}			1.5	4.7		5.9	1.4	3.5	4.7	5.8	
t_{PHZ}	$\overline{OE}$	Y	2	5.3		5.7	2	3.6	5.2	5.5	ns
t_{PLZ}			1.9	4.6		4.6	1.9	3.2	4.4	4.4	

† All typical values are at V_{CC} = 3.3 V, T_A = 25°C.

PRODUCT PREVIEW


PRODUCT PREVIEW Information concerns products in the formative or design phase of development. Characteristic data and other specifications are design goals. Texas Instruments reserves the right to change or discontinue these products without notice.

PARAMETER MEASUREMENT INFORMATION




TEST	S1
t_{PLH}/t_{PHL}	Open
t_{PLZ}/t_{PZL}	6 V
t_{PHZ}/t_{PZH}	GND


LOAD CIRCUIT FOR OUTPUTS




VOLTAGE WAVEFORMS
PULSE DURATION



VOLTAGE WAVEFORMS
SETUP AND HOLD TIMES



VOLTAGE WAVEFORMS
PROPAGATION DELAY TIMES
INVERTING AND NONINVERTING OUTPUTS



VOLTAGE WAVEFORMS
ENABLE AND DISABLE TIMES
LOW- AND HIGH-LEVEL ENABLING

NOTES: A. C_L includes probe and jig capacitance.
B. Waveform 1 is for an output with internal conditions such that the output is low except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high except when disabled by the output control.
C. All input pulses are supplied by generators having the following characteristics: PRR ≤ 10 MHz, Z_O = 50 Ω, t_r ≤ 2.5 ns, t_f ≤ 2.5 ns.
D. The outputs are measured one at a time with one transition per measurement.

Figure 1. Load Circuit and Voltage Waveforms

Unikeyic Electronics

Global Electronic Components Distributor

Click to view pricing, inventory, delivery, and lifecycle information:

Texas Instruments:

BQ24314DSGR MSP430F2001TRSAT MSP430F47127IPZ MSP430F5172IRSBT TLC085CDR ADS8344E UCC27210DR OPA2541BM LMV358MMX/NOPB TPS7A8018DRBR UA9637ACPS OPT3101RHFR TPS51125ARGER TPS92200D2DDCR DS90C383MTDX/NOPB SN75LV4735DBLE TCAN332DR MSP430F2112TRHBT MSP430G2332IN20 MSP430G2403IPW28 OPA643P SN74GTL2006PWR SN74LVCZ240APW TPS71710DCKR CC2520RHDR ISO124U/1K PCM56U TLV990-28PFB TPA6203A1DRBR MSP430F5131IDA