
Fair-Rite Products Corp.
Your Signal Solution®
Ferrite Components for the Electronics Industry
Fair-Rite Products Corp. PO Box J,One Commercial Row, Wallkill, NY 12589-0288
Phone: (888) 324-7748 www.fair-rite.com

Fair-Rite Product's Catalog
Part Data Sheet, 2508053007Y0
Printed: 2013-07-03



Part Number:	2508053007Y0
Frequency Range:	Low Current
Description:	MULTI-LAYER CHIP BEAD
Application:	Suppression Components
Where Used:	Board Component
Part Type:	Chip Beads

Mechanical Specifications

Weight: .010 (g)

Part Type Information

Fair-Rite offers a broad selection of cost effective multi-layer chip beads to suppress conducted EMI signals. Chip beads can be used in an array of devices such as cellular phones, computers, laptops, pagers, etc. The small package sizes accommodate automated placements and allow for a dense packaging of circuit boards. Chip beads are 100% tested for impedance and dc resistance. They are available in standard, high and GHz signal speeds. The multi-layer chip beads are organized by increasing package size and current carrying capacity.

-All multi-layer chip beads are supplied taped and reeled, if required bulk packed chip beads can be provided.

-The impedance values listed are typical values. The nominal impedance with a ± 25% tolerance is specified for the + marked 100 MHz. Chip beads are measured for impedance on the HP 4291A and fixture HP 16192A.

-Chip beads have plated contacts, 100% tin over a nickel undercoating. They can accommodate both reflow and wave soldering technologies.

-The suggested land patterns are in accordance to the latest revision of IPC-7351.

-Recommended storage and operating temperature range is -55°C to 125°C.

-Our 'Chip Bead Kit' (part number 0199000018) is available for prototype evaluation.

Fair-Rite Products Corp.
Your Signal Solution®
Ferrite Components for the Electronics Industry
Fair-Rite Products Corp. PO Box J,One Commercial Row, Wallkill, NY 12589-0288
Phone: (888) 324-7748 www.fair-rite.com

Fair-Rite Product's Catalog
Part Data Sheet, 2508053007Y0
Printed: 2013-07-03

Mechanical Specifications

Dim	mm	mm tol	nominal inch	inch misc.
A	0.90	±0.20	0.035	-
B	1.25	±0.20	0.049	-
C	2.00	±0.20	0.079	-
D	0.50	±0.30	0.020	-
E	-	-	-	-
F	-	-	-	-
G	-	-	-	-
H	-	-	-	-
J	-	-	-	-
K	-	-	-	-

Electrical Specifications

Typical Impedance (Ω)	
50 MHz	22
100 MHz+	30 ±25%
500 MHz	46
1000 MHz+	-

Electrical Properties	
Signal Speed	Standard
Max DCR (Ω)	0.10
Max Current (mA)	300

Land Patterns

V	W ref	X	Y	Z
0.600 0.024	1.900 0.075	1.500 0.059	1.300 0.051	- -

Winding Information

Turns Tested	Wire Size	1st Wire Length	2nd Wire Length
-	-	-	-

Reel Information

Tape Width mm	Pitch mm	Parts 7 " Reel	Parts 13 " Reel	Parts 14 " Reel
8	4	4000	10000	-

Package Size

Pkg Size
0805 (2012)

Connector Plate

# Holes	# Rows
-	-

Legend

+ Test frequency

Preferred parts, the suggested choice for new designs,have shorter lead times and are more readily available.

The column H(Oe) gives for each bead the calculated dc bias field in oersted for 1 turn and 1 ampere direct current. The actual dc H field in the application is this value of H times the actual NI (ampere-turn) product. For the effect of the dc bias on the impedance of the bead material, see figures 18-23 in the application note How to choose Ferrite Components for EMI Suppression.

A ½ turn is defined as a single pass through a hole.

Σl/A - Core Constant

l_e: Effective Path Length

A_e: Effective Cross-Sectional Area


V_e: Effective Core Volume

A_L - Inductance Factor $\left(\frac{L}{N^2}\right)$


NI - Value of dc Ampere-turns

N/AWG - Number of Turns/Wire Size for Test Coil

Fair-Rite Products Corp.
Your Signal Solution®
Ferrite Components for the Electronics Industry
Fair-Rite Products Corp. PO Box J,One Commercial Row, Wallkill, NY 12589-0288
Phone: (888) 324-7748 www.fair-rite.com



Impedance, reactance, and resistance vs. frequency.



Impedance vs. frequency with dc bias.

Unikeyic Electronics

Global Electronic Components Distributor

Click to view pricing, inventory, delivery, and lifecycle information:

Fair-Rite:

5943011101 5975001101 0199000005 0461178181 2743002112 5961003801 0446164951 0446167281
2944666661 2867000102 2873006802 4077296011 2643626502 2643801002 444173951 5943000501
5943018601 2643801102 2661000801 2673022401 2677006302 5943000911 5977001721 2675665702
2675821502 2961666631 5977000301 5978003801 0444177081 3078990851