SD008-2161-112



FEATURES

- Schottky-Type Photodiode
- Photovoltaic Mode Operation
- Low Noise
- High Speed
- Visible Blindness
- Isolated Anode and Cathode

DESCRIPTION

The SD008-2161-112 is a GaN UVB photodiode with a 0.076 mm^2 active area. Unlike most UV detectors it cuts off unwanted visible light from its detection spectrum (220-320nm), thereby eliminating the need for optical filter. Photodiode is assembled in a hermetic TO-46 package.

APPLICATIONS

- UVB Detection and Monitoring
- Medical
- Military

> Absolute Maximum Ratings

Part No.	Wavelength Range [nm]	Reverse Voltage [V]	Operating Temperature [C]	Storage Temperature [C]	Package
SD008-2161-112	240 to 320	5	-40 to +85	-55 to +125	TO-46

> Electrical and Optical Characteristics


Typical Characteristics (T=23°C unless specified)						
Parameter	**Test Conditions**	**Symbol**	**Min**	**Typical**	**Max**	**Unit**
Dark Current	V_R =0.1V	I_d	-	1	100	pA
Diode Capacitance	V_{bias} = 0V; f = 1 MHz	C_D	-	5	-	pF
Short Circuit Current	UVI=1.0	I_{sc}	-	20	-	nA
Peak Spectral Sensitivity	λ= 300nm, V_R = 0 V	λ_p	-	0.1	-	A/W
Rise Time		T_r	-	1	-	ns
Fall Time		T_f	-	1	-	ns
Shunt Resistance	V_R = 10mV	R_{sh}	1	100	-	GΩ
Noise Equivalent Power	λ= 300nm	NEP	-	1.6	-	$10^{-17}W/Hz^{0.5}$

Advanced Photonix, 1240 Avenida Acaso, Camarillo CA 93012 • Phone (805) 987-0146
http://www.advancedphotonix.com/


Rev 5/9/2019

© 2018 Advanced Photonix. All rights reserved.

> Spectral Response




> UV-A Photocurrent




Advanced Photonix, 1240 Avenida Acaso, Camarillo CA 93012 • Phone (805) 987-0146
http://www.advancedphotonix.com/

Rev 5/9/2019
© 2018 Advanced Photonix. All rights reserved.

> UV-I Photocurrent



> Noise vs. Bias




Advanced Photonix, 1240 Avenida Acaso, Camarillo CA 93012 • Phone (805) 987-0146
http://www.advancedphotonix.com/

Rev 5/9/2019

© 2018 Advanced Photonix. All rights reserved.

> TO-46 Window Cap [SD008-2161-112]



>Soldering Conditions: 260˚C 1/16 inch away from case for 3 seconds max.

LEGAL DISCLAIMER

All products, product specifications, and data are subject to change without notice to improve reliability, function, design, or otherwise. Advanced Photonix, its affiliates, agents, employees and all persons acting on its or their behalf (collectively, "Advanced Photonix"), disclaim any and all liability for any errors, inaccuracies or incompleteness contained in any datasheet or in any other disclosure relating to any product. Advanced Photonix makes no warranty, representation or guarantee regarding the suitability of the products for any particular purpose or the continuing production of any product. To the maximum extent permitted by applicable law, Advanced Photonix disclaims (i) any and all liability arising out of the application or use of any product, (ii) any and all liability, including without limitation special, consequential or incidental damages, and (iii) any and all implied warranties, including warranties of fitness for particular purpose, non-infringement and merchantability Statements regarding the suitability of products for certain types of applications are based on Advanced Photonix's knowledge of typical requirements that are often placed on Advanced Photonix products in generic applications. Such statements are not binding statements about the suitability of products for a particular application. It is the customer's responsibility to validate that a particular product with the properties described in the product specification is suitable for use in a particular application. Parameters provided in datasheets and / or specifications may vary in different applications and performance may vary over time. All operating parameters, including typical parameters, must be validated for each customer application by the customer's technical experts. Product specifications do not expand or otherwise modify Advanced Photonix's terms and conditions of purchase, including but not limited to the warranty expressed therein. Except as expressly indicated in writing, Advanced Photonix products are not designed for use in life-saving, or life-sustaining applications, or for any other application in which the failure of the Advanced Photonix product could result in personal injury or death. Customers using or selling Advanced Photonix products not expressly indicated for use in such applications do so at their own risk. No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document or by any conduct of Advanced Photonix. Product names and markings noted herein may be trademarks of their respective owners.

MATERIALS SAFETY

This product is free of conflict minerals and meets REACH compliance. Please see website for reports.

Advanced Photonix, 1240 Avenida Acaso, Camarillo CA 93012 • Phone (805) 987-0146
http://www.advancedphotonix.com/

Rev 5/9/2019

© 2018 Advanced Photonix. All rights reserved.

Unikeyic Electronics

Global Electronic Components Distributor

Click to view pricing, inventory, delivery, and lifecycle information:

Advanced Photonix:

NSL-4960 PDV-P5002 PDV-P8101 PDV-P9004 100-12-22-021 PDB-C613-2 PDV-P9002 0090-3111-185 APX-SC0010 NSL-5540 076-14-21-011 NORPS-12 NSL-19M51 NSL-32SR2 PDB-C154SM PDB-V615-2 PDV-P9200 NSL-5150 PDV-P9203 019-111-411 100-41-21-231 SD019-141-411-G SD200-12-22-041 PDV-P9008 0050-3111-111 019-141-411-G 118-23-21-021 NSL-32SR3 NSL-5910 PDV-P8006